

MODEL M2 TRANSFORMER for 'O' GAUGE CONTROLLERS

WARNING: - THIS APPLIANCE MUST BE EARTHED. FOR INDOORS USE ONLY.

The controller should be regularly examined for potential hazards such as damage to the casing, cable or plug. In the event of any damage, the unit should not be used until the damage has been repaired and the unit should not be opened as it has no consumer repairable components. A repair service is available at the address shown below.

MAINS CABLE:


This unit is presently fitted with a 3 amp fused plug. If this plug is not suitable for your supply, another plug must be fitted in the following manner: -

BLUE: To the small pin marked 'N' or coloured **Black**.

BROWN: To the small pin marked 'L' or coloured **Red**.

GREEN/YELLOW: To the large pin marked 'E' or by the symbol \perp or coloured **Green** or **Green/Yellow**.
If any other type of plug is used, a 3 Amp fuse must be used in the mains circuit. If in doubt consult an electrician.

CAUTION: It is very important that the outputs of two or more control units are not connected together in parallel. i.e. both wires. If this is done, there is a risk of electric shock from a plug not inserted into a socket.




OUTPUT:

Output 18v AC , 2.5 amps maximum @25 deg C.

Protected by automatic resetting circuit breaker.

Suitable for the following Gaugemaster Controllers and accessories: - 100.O, UO and other accessories.

This unit has a single secondary winding and is only suitable for powering one single track controller, if powering point motors we recommend using a CDU to avoid voltage drop to the track.



GUARANTEE:

We undertake to replace, free of charge, any parts found defective within the lifetime of the unit, providing the item has not been tampered with and parts are still available for such a repair. This guarantee covers only the supply of replacement parts, labour cost for fitting of same and the cost of returning the unit to the customer or retailer. This Guarantee does not affect your Statutory Rights.

We reserve the right to vary design or specification without notice.

CONSTRUCTED TO EN60 742

A CATALOGUE ON THE FULL RANGE OF GAUGEMASTER PRODUCTS IS AVAILABLE

GAUGEMASTER CONTROLS Ltd Gaugemaster House, Ford Road, Arundel, West Sussex, BN18 OBN.

Tel. No: 01903 884321 Fax. No: 01903 884377 Email gaugemaster@gaugemaster.co.uk Web site www.gaugemaster.co.uk

Registered in England. Reg. No: 2714470.

